#### M. K. JUCHHEIM GmbH & Co

Delivery address:Mackenrodtstraße 14, 36039 Fulda, Germany

Postal address: 36035 Fulda, Germany
Phone: +49 661 60 03-0
Fax: +49 661 60 03-6 07
E-mail: mail@jumo.net
Internet: www.jumo.net

#### JUMO Instrument Co. Ltd.

JUMO House Temple Bank, Riverway Harlow, Essex CM 20 2TT, UK

Phone: +44 12 79 63 55 33 Fax: +44 12 79 63 52 62 E-mail: sales@jumo.co.uk

#### JUMO PROCESS CONTROL INC.

885 Fox Chase, Suite 103 Coatesville PA 19320, USA Phone: 610-380-8009 Fax: 610-380-8009 E-mail: info@JumoUSA.com

Internet: www.JumoUSA.com



Data Sheet 40.4387

Page 1/4

# Pressure transmitter JUMO dTRANS p02 CERAMIC

Type 404387

# **General application**

The JUMO dTRANS p02 CERAMIC pressure transmitter measures the gauge (relative) or absolute pressure in both corrosive and non-corrosive gases, vapors and liquids. The ceramic-based measuring system in this pressure transmitter operates on the principle of capacitive measurement. The output signal is a DC current that is proportional to the input pressure.

#### The display can show:

- pressure in 13 different dimensional units, measurement in % or scaled with a freely selectable unit, output current in mA
- sensor temperature in °C or °F
- measurement error, out-of-range measurement
- minimum and maximum pressures (peak-reading indicator)
- pressure and sensor temperatures can be shown simultaneously (on 2 lines)

#### The keys can be used to set up:

- start and end of measurement, with pressure input
- start and end of measurement, without pressure input (blind setting)
- damping or time constant
- current generator function
- output signal on error
- key inhibit
- reset min. and max. measurements (peak-reading indicator)
- density correction for different measurement media
- display of the media temperature in °C or °F

The JUMO dTRANS p02 CERAMIC pressure transmitter can also be operated through a HART® communicator, or a PC in conjunction with a HART® modem and the JUMO setup program running under Windows®.





# **Accessories**

#### Setup program

Sales No. 40/00365072

The setup program for all instruments in the JUMO dTRANS p02 series has been created according to the VDI/VDE 2187 user interface. In conjunction with the HART® modern, the program enables convenient operation and parameter setting of the pressure transmitter from a PC.

#### HART® modem

Sales No. 40/00345666

The HART® modem forms the link between the JUMO dTRANS p02 pressure transmitter and the serial interface of a PC.

# **Technical data**

#### Reference conditions

as per DIN 16086 and IEC 770/5.3

# Nominal input range

see Order details

# Range setting

The measurement range can be set from the keys on the pressure transmitter, by using the setup program or a HART® communicator as described below:

Start and end of the measurement range can be continuously adjusted within the nominal range. The span of the measurement should not be less than 10% of the nominal range.

≺	Nominal range	>		
	Span			
≺	≻ Range	<b>≺</b> ≻		
Start		End		
(4 mA)		(20 mA)		

# Displayable units

Input pressure:

mH<sub>2</sub>O, inH<sub>2</sub>O, inHg, ftH<sub>2</sub>O, mmH<sub>2</sub>O, mm Hg, psi, bar, mbar, kg/cm<sup>2</sup>, kPa, Torr, MPa; Measurement:

% or scaled with freely adjustable dimensional unit

Output current:

mΑ

# Additional displays

Indication of the sensor temperature, minimum pressure, maximum pressure. Indication of overrange or error

# **Density correction**

adjustable over the range from 0.100 to  $5.000 \, kg/dm^3$ 

#### **Overload limits**

see Order details

#### **Bursting pressure**

for all ranges: 150 bar

#### Parts in contact with the medium

standard:

stainless steel, Mat. Ref. 1.4571 aluminium oxide  $Al_2O_3$  (96%), FPM (Viton®), others on request

#### **Pressure connection**

see Order details

#### Output

4-20mA burden ≤ (U<sub>B</sub>-11.5V) / 0.022A burden with HART®: max. 1100Ω, min. 250Ω with HART® protocol V 5.3. Complies with the guidelines of the HCF (HART® Communication Foundation)

#### **Burden error**

< 0.1%

# Zero offset / adjustment accuracy

 $\leq 0.01\,\text{mA}$ 

#### Ambient temperature error

over the compensated temperature range from -20 to +85°C

zero: ≤ 0.005% per °C typical,

≤0.01% per °C max.

span: ≤ 0.005% per °C typical,

≤0.01% per °C max.

#### **Deviation from characteristic**

for limit point adjustment:

≤ 0.1% of full scale of nominal range; as per DIN 16086

#### **Hysteresis**

≤ 0.02% of full scale

## Reproducibility

≤ 0.02% of full scale

#### Response time

approx. 150 msec without damping

#### Damping

adjustable from 0 - 100 sec

#### Stability over 1 year

 $\leq$  0.1% of full scale (for nominal range, and under reference conditions as per I EC770)

#### Supply voltage

11.5 - 36V DC

#### Note:

at least 17V DC (250 $\Omega$ ) for communication using the HART® protocol.

#### Supply voltage error

≤ 0.1% of full scale per 10V change (nominal supply voltage 24V DC)

#### Permissible ambient temperature

-40 to +85°C; as per DIN 16086 (it may be impossible to read the LCD display at temperatures below -20°C)

# Storage temperature

-40 to +85°C

# Permissible temperature of medium

-40 to +120°C

## Electromagnetic compatibility (EMC)

as per EN 61 326

#### Mechanical shock

50g/11msec

#### Mechanical vibration

max. 5g over 10-2000Hz

#### **Protection**

with connecting cable IP65 to EN 60529

# Insulation resistance

100MΩ; 50V DC

### **Breakdown strength**

 $\geq$  500  $V_{eff}$ 

#### Housing

aluminium die-casting GDAISi12

#### Climatic conditions

 $\leq 80\%$  rel. humidity with condensation, annual mean

#### **Electrical connection**

clamping case with screwed cover, 2 poles and earthing terminal, plastic cable gland  $M20 \times 1.5$  for cable diameters 6 to 12mm

#### **Nominal position**


ex-factory, upright vertical (pressure connection below) any operating position

#### Weight


approx. 1.5kg

# HART® communication


# between PC and pressure transmitter





## between HART® communicator and pressure transmitter





# **Dimensions**

















NTS	DN	D <sub>1</sub>	D <sub>2</sub>	$D_3$	D <sub>4</sub>	h <sub>1</sub>	h <sub>2</sub>
606	40	Ø48	Ø56	RD 65 x 1/6	Ø78	10	21
607	50	Ø61	Ø68.5	RD 78 x 1/6	Ø92	11	22


# **Electrical connection**

Connection		Terminals
Supply 11.5 — 36 V DC, 11.5 — 30 V DC for intrinsically safe version	<u>.</u>	1 L+ 2 L-
Output 4 — 20 mA 2-wire	<u>.</u>	1 L+ proportional current 4 — 20 mA 2 L- in supply
Test connection, current output	internal resistance of ammeter $\leq$ 10 $\Omega$	TEST + TEST -
Test connection, HART®		TEST + HART®
Shielding		<b>(1)</b>

# Caution:

Earth the instrument! (pressure connection and shielding)

# Terminals



# **Order details**

#### Basic type 404387 Pressure transmitter dTRANS p02 CERAMIC with capacitive-ceramic measuring system Basic type extensions none Nominal input range -100 to 100 mbar (overload limits -1 and 6 bar) 414 gauge pressure -0.6 to 0.6 453 (overload limits -1 and 10 bar) bar gauge pressure 457 -1 to 4 bar gauge pressure (overload limits -1 and 40 bar) 461 -1 to 25 bar gauge pressure (overload limits -1 and 60 bar) 0 to 0.6 absolute pressure (overload limits -1 and 10 bar) 487 bar 491 absolute pressure (overload limits -1 and 40 bar) 0 to 4 bar 495 0 to 25 bar absolute pressure (overload limits -1 and 60 bar) Output 405 4 - 20 mA with HART® protocol **Process connection** $\frac{1}{2}$ " pipe to EN 837 $\frac{11}{2}$ - $\frac{111}{2}$ NPT 504 515 $11/_{2}^{2}$ " pipe to DIN 3852 570 606 taper connection with ring nut DN40 to DIN 11851 607 taper connection with ring nut DN50 to DIN 11851 clamp connection DN50 to DIN 32676 616 653 tank connection with ring nut DN40 Material for process connection stainless steel, Mat. Ref. 1.4571 99 special material for process connection Seal 601 FPM (Viton®) 604 FFPM (Kalrez®) on request **Electrical connection** 06 screw terminals 99 special electrical connection 404387 / 0 405 Order code

# Factory setting:

Please specify the range to be set and the dimensional unit in plain text.